Proceedings of the 4th International Conference on Computing Innovation and Applied Physics
DOI: 10.54254/2753-8818/80/2025.GL20478

Research on the Application and Optimization of Stepper Motors in Ink jet Printers

Qi Liu[1,a,*]

[1]*School of New Oriental, Guangzhou, 510000, China*
a. LiuQi825713@outlook.com
**corresponding author*

Abstract: Ink jet printers have become an indispensable tool in various fields due to their high resolution, cost-effectiveness, and versatility. The performance of these printers heavily relies on precise mechanical control. Stepper motors, as key actuators in these systems, play a vital role in ensuring smooth operation and maintaining print quality. Understanding and optimizing these components are essential for addressing the growing demands for speed, accuracy, and energy efficiency in modern printing technologies. This article explores the basic structure of ink jet printers, analyzes their application functions, and focuses on the driving mechanism of print heads and paper transport systems. Studied the components, operating modes, and principles of the stepper motors used in these devices, emphasizing their functionality based on electromagnetic induction. In addition, this article proposes optimization strategies aimed at improving the accuracy and speed control of stepper motors in ink jet printers. Experimental data shows that through these optimizations, performance and response time have been significantly improved. The research results emphasize that the integration of enhanced stepper motor technology not only improves the market competitiveness of ink jet printers, but also promotes technological innovation and industrial progress.

Keywords: Ink jet printer, stepper motor, electromagnetic induction, accuracy

1. Introduction

With the rapid advancement of technology and the evolution of modern society, printing technology continues to undergo significant updates and developments. Among these innovations, ink-jet printing technology and machines have garnered widespread attention due to their integral role in both office and home environments. The performance and quality of ink-jet printers are crucial, as they directly influence the user experience. A key component within these printers is the stepper motor, whose structure and operational principles play a pivotal role in determining the efficiency and effectiveness of the printing process [1].

This paper aims to explore the fundamental structure of ink-jet printers and the various types of stepper motors utilized within them. This paper examine the working principles of these motors, while also addressing current technical challenges and proposing optimization strategies. Specific areas of focus will include precision control and speed control issues and optimization solutions, all of which are critical factors in enhancing printer performance.

© 2025 The Authors. This is an open access article distributed under the terms of the Creative Commons Attribution License 4.0 (https://creativecommons.org/licenses/by/4.0/).

DOI: 10.54254/2753-8818/80/2025.GL20478

By delving into these topics, this paper seeks to deepen our understanding of both ink-jet printers and stepper motors, subsequently providing valuable insights and potential solutions for optimizing motor performance. This paper goal is to facilitate ongoing progress and development in ink-jet printing technology, while offering effective strategies for professionals in related industries. Through collaboration and innovation, hoping this article will contribute to the continuous progress of the entire printing technology

2. Basic Analysis of ink-jet printer

2.1. Basic structure of ink-jet printer

Firstly, the core of ink jet printer is printing head. It is used to spray ink onto key components of paper. Print head generally consist of multiple nozzles. It can quickly open and close in the process of printing and spray ink onto paper precisely. Modern print head adopts the technology of micro piezoelectric. It can achieve high-precision and high-velocity operation and guarantee the clear and delicate of pictures and worlds [2].

Secondly, ink box is a important component of ink jet printer. It stores ink for printing, usually classified into black and color box. The types and capacities of ink box are different. Some are disposable products, while others can be replaced with ink. Clients can choose suitable in box which can satisfy their needs. Resulting in reduction of costs and improvement of printing efficiency.

Thirdly, transmission system is the mechanism that enables paper movement during the printing process. Ink jet printers generally use conveyor belts or rollers, conveying papers onto printing areas from paper inlet. The accuracy of transmission systems directly affects the quality and speed of printing. When the transmission systems are more precise, the papers can be more stably positioned during the printing process, leading to achievement of higher printing accuracy [3].

In addition, control circuit is also an indispensable part of ink jet printer. It is used to receive print instructions from computers or other devices and transform them to the control signals of print head movement and ink spray. Modern ink jet printers are equipped with advanced micro-CPU and memory to ensure fasting processing and sensitive response [4].

Furthermore, the shell and printing interface determine the way user interact with the printer. Shells not only provide mechanical protection, but also influence the appearance design of printer. Interface likes LCD screen or buttons enable directly perform operation settings. Users can check printing condition and perform maintenance management.

Finally, software driver program is a bridge to connect computers with printers. It is responsible for parsing print data and performing format conversion, as well as optimizing print settings to achieve the best printing results [5]. The detailed structure is shown in Figure 1.

DOI: 10.54254/2753-8818/80/2025.GL20478



Figure 1: Basic structure of ink-jet printer

From the perspective of printing speed, the printing speed of ink jet printer are slow, especially when printing high-quality images. The printing speed of laser printer are fast, suitable for the office environment which needs for fast output.

Therefore, the ink jet printers are suitable for domestic using, photograph, art works and other scenes which need high-quality color output. Laser printers are suitable for offices, enterprises and other environments which needs print a large number of documents. Thermal printers commonly are used to shops, restaurants and other commercial occasions.

2.2. Comparison with other printers

From the perspective of printing technology, ink jet printers spray liquid ink onto paper through a nozzle. Therefore, it can achieve high-resolution color printing, suitable for printing photos and images. Laser printers transfer electrostatic images onto toner using a laser beam, and then transfer the toner onto paper by heating it. Therefore, the printing speeds are very fast, suitable for printing large amounts of text. Thermal printers change color by heating the coating special paper. Therefore, it commonly used for printing labels and receipts.

From the perspective of printing quality, ink jet printers have bright colors and rich details, suitable for some images and photos that require high image quality. Laser printers can print clearer text, suitable for reports and documents, and color laser printer can achieve higher image quality. The image pixels printed by thermal printers are relatively low, so they are mainly used for simple text and bar codes.

From the perspective of costs, ink jet printers int initial purchase cost is relatively low, but the prices of ink are high. The cost which are long-term using is relatively high. The laser printers' initial investments are high, but carbon powders can be used for a long time, the cost of printing separate page is relatively low. The cost of thermal printers is relatively low, but the consumption of printing paper also needs to be considered.

From the perspective of printing speed, the printing speed of ink jet printer are slow, especially when printing high-quality images. The printing speed of laser printer are fast, suitable for the office environment which needs for fast output [6].

Therefore, the ink jet printers are suitable for domestic using, photograph, art works and other scenes which need high-quality color output. Laser printers are suitable for offices, enterprises and other environments which needs print a large number of documents. Thermal printers commonly are

DOI: 10.54254/2753-8818/80/2025.GL20478

used to shops, restaurants and other commercial occasions. Comparison with other printers is shown in Table 1.

Table 1: Comparison with other printers

	Printing technology	Print quality	Cost	Print speed
Ink jet printer	Using a nozzle to transfer liquid Ink is sprayed onto the paper	Vibrant colors and rich details, suitable for images and photos that require high image quality	The initial purchase cost is low, but the price of ink consumables is high, resulting in higher long-term usage costs	Usually slow, especially when printing high-quality images
Laser printer	Transfer electrostatic images onto carbon powder using a laser beam, and then transfer the carbon powder onto paper by heating	The printed text is clear and suitable for documents and reports, and color laser printers can also achieve good image quality	The initial investment is high, and the cost of printing a single page is low	Fast printing speed, suitable for office environments that require fast output
Thermal printer	By heating the coating on special paper to change its color	Low image quality, mainly used for simple text and barcodes	Generally low cost, suitable for specialized scenarios (such as supermarket cashiers)	Fast printing speed, suitable for occasions that require instant printing

3. Basic Analysis of Stepper motor

3.1. Working principle and mechanism

Stepper motor is one of the indispensable components in ink jet printers, its main function is to drive the print head and paper transport. In terms of driving the print head, the stepper motor converts electronic pulses into corresponding angles or distances to achieve left and right movement of the print head. In practical situations, the movement of the print head is achieved by driving the belt and pulley through a stepper motor. Firstly, the controller sends a pulse signal to control the rotation of the stepper motor. Each pulse corresponds to a step of the motor, and the frequency and duration of the control signal determine the movement speed and position of the print head. Ink jet printers typically use nozzles to gradually print within the printing area. Therefore, the stepper motor can control the nozzle to accurately reach the corresponding position, thereby achieving high-quality image output.

In terms of paper transportation, stepper motors can transport paper to the corresponding position and ensure accurate positioning of the paper. At the beginning of printing, the stepper motor will receive a signal from the printing control to start the operation of paper transportation. The motor transmits force to the roller or conveyor belt through a pulley or gear system, pushing the paper towards the print head. In addition, the control system of the stepper motor can adjust the movement speed and stride according to printing requirements to adapt to different paper specifications and printing tasks.

The structural composition of stepper motors significantly influences their performance characteristics, and the specifics of these structures can also impact the motor's control methodologies.

DOI: 10.54254/2753-8818/80/2025.GL20478

Although various types of stepper motors share common components, substantial variations may exist in their hardware configurations.

3.2. Components and types of stepper motor

The basic structure of a stepper motor typically consists of front and rear end caps, bearings, a central shaft, rotor core, stator core, corrugated washers, and fasteners. The front and rear end caps function as protective enclosures for the internal components of the stepper motor, securing the motor's core elements while simultaneously serving to shield against the ingress of external contaminants such as dust and pollutants.

Bearings are integral to minimizing frictional forces during rotor rotation, providing support for the central shaft of the motor. Typically, these bearings are positioned at both ends of the motor shaft to ensure smooth rotational movement.

The central shaft acts as the primary rotating component of the motor, establishing a connection with the rotor. The interaction between the rotor and the stator is pivotal, as this interaction is what ultimately drives the rotor's rotation. Corrugated washers, designed to function as elastic spacers, play a critical role in mitigating vibrations and noise that may arise during motor operation, thereby contributing to the motor's overall stability. The basic structure of a stepper motor is shown in Figure 2.



Figure 2: The basic structure of a stepper motor

The rotor and stator are the core components in a motor, and the core of the working principle of a stepper motor is also about the interaction between the rotor and stator. Firstly, in a basic stepper motor, there are six stator tooth coils that form three sets of electromagnetic coils. Therefore, when a current passes through, magnetism can be generated and N and S poles can be formed. When the direction of the current is changed, the magnetic poles will also change [7]. In the middle of it is a rotor made up of stacked steel plates. So in the simplest stepper motor, there are four rotors and six stators.

3.3. Precise control

After energizing coil, a while keeping the stator stationary, the rotor initially aligns with coil A. Subsequently, when de energizing coil A and energizing coil B, the rotor rotates 30 ° to align with

DOI: 10.54254/2753-8818/80/2025.GL20478

the magnetic field generated by coil B. Afterwards, coil B was powered off and coil C was activated, causing the rotor to undergo another rotation adjustment while seeking alignment with coil C. This operation sequence represents a full step rotation mode, where the rotor advances in discrete steps of 30°.

In order to achieve a narrow operating angle of 15°, it is necessary to keep coil A energized while keeping coil B deactivated when the rotor is aligned with coil A. Under these conditions, the rotor will rotate 15° between coils a and B. Subsequently, coil a is deactivated while coil B remains energized, causing the rotor to rotate another 15° to achieve alignment with coil B. After rotation, coil C is activated, causing the rotor to rotate another fifteen degrees to align with coil C. This sequential activation method helps the motor to rotate continuously at a step angle of 15°. This working method is called the half step mode. The simplest stepper motor is shown in Figure 3 [8].



Figure 3: The simplest stepper motor

In contemporary applications, hybrid stepper motors are extensively utilized due to their distinctive structural characteristics. The rotor is constructed as a permanent magnet unit, featuring a north (N) pole at one end and a south (S) pole at the opposite end, with a total of 50 teeth distributed along its periphery. The stator comprises a configuration of eight coils, organized into two groups of four coils each, and is equipped with a total of 48 teeth. Upon activation of the coils, the rotor experiences a rotation corresponding to a step angle of 1.8 degrees [9]. The S pole of the rotor aligns with the nearest N pole of the stator, while the N pole located at the rear of the rotor aligns with the S pole of the stator, resulting in enhanced accuracy and torque generation [10]. Hybrid stepper motor is shown in Figure 4.



Figure 4: Hybrid stepper motor

DOI: 10.54254/2753-8818/80/2025.GL20478

Furthermore, hybrid stepper motors operate in multiple modes, including full-step mode and half-step mode, which facilitate more precise angular movement. These operational modes contribute to the motor's capability to perform high-precision tasks effectively.

Stepper motors, while widely utilized in various applications, encounter several significant challenges related to precision and stability. Firstly, the accuracy of a stepper motor is predominantly influenced by its stepping angle, which typically ranges from 1.8 degrees to 0.9 degrees. However, in practical applications, factors such as variations in load, friction, and an unstable power supply can lead to step loss, resulting in positional errors. This phenomenon becomes particularly pronounced in high-speed operations or under heavy loads, directly impacting the overall accuracy and reliability of the system.

Technical issues and optimization solutions

In the context of ship stepper motors, this study begins with the simulation of the motor followed by the development of a comprehensive mathematical model. Subsequently, system identification techniques are applied to the stepper motor to characterize its behavior accurately [11]. An optimized controller is then designed for the ship's stepper motors based on the results obtained from the system identification process, and a series of experiments are conducted to validate the effectiveness of the proposed control strategy.

The experimental methodology first involves measuring the response speed of the stepper motor under normal operating conditions. Following this, intentional disturbances are applied to assess the controller's performance in terms of its ability to maintain stability and adjust effectively in the presence of interference. The experimental findings reveal that through optimization of the positioning of the ship's stepper motor, the achieved response speed can be minimized to 6.35 ms. This response speed is significantly lower than those obtained using conventional digital control technologies and microcontroller-based methods [12].

Consequently, the results indicate that enhancing the positional accuracy of the ship's stepper motor not only contributes to a reduction in response time but also facilitates improved time adjustment capabilities in the system. This study underscores the importance of system identification and optimization in the advancement of stepper motor control in maritime applications [1].

Additionally, vibrations and noise generated during motor operation warrant consideration. External disturbances or fluctuations within the motion control system can contribute to unstable operation, resulting in excessive oscillations and noise generation. Such factors not only impair the performance of the system itself but also accelerate wear on motor components, thereby reducing the overall service life of the equipment.

To optimize speed control of stepper motors and enhance their operational stability, this study presents a Particle Swarm Optimization (PSO) fuzzy PID control algorithm [13]. PSO, a swarm intelligence-based optimization technique introduced by Kennedy and Eberhart in 1995, emulates the foraging behavior of bird flocks and the schooling behavior of fish to identify optimal solutions [14]. This algorithm mirrors predatory behaviors found in nature when addressing optimization challenges for unknown functions.

In the PSO framework, each "particle" represents a potential solution characterized by its current position, velocity, and historical best position. The iterative process involves updating the velocity and position of each particle continuously. The present work employs the PSO algorithm to refine the parameters of a fuzzy PID controller. Typically, a PID controller serves as a widely used feedback mechanism, and its parameters can be customized to suit the specific requirements of a system. The integration of fuzzy logic into the PID control paradigm enhances the controller’s capacity to manage nonlinear, time-varying behaviors, and other complexities inherent in various systems [15].

The proposed PSO fuzzy PID stepper motor speed control system utilizes an STM microcontroller as the primary control chip. This system comprises several key components, including a main control

DOI: 10.54254/2753-8818/80/2025.GL20478

module, a driver module, a startup module, a power module, an optocoupler isolation module, and a driver. During operations, the main control module derives control signals by employing a table lookup method based on the discrepancy between the actual pulse count and the target pulse count, subsequently generating the requisite number of pulses to regulate the stepper motor's speed.

Moreover, the upper computer's monitoring module enables users to continuously read and record the speed data of the stepper motor in real time. For instance, in scenarios where the target speed is set to 10 rad/s, the system can effectively demonstrate the speed control outcomes of traditional PID control, fuzzy PID control, and PSO-fuzzy PID control. Experimental results indicate that the stepper motor achieves stable speed regulation in the least amount of time without oscillation when governed by the PSO-enhanced fuzzy PID algorithm. This strategy facilitates efficient management of stepper motor speeds, representing a significant advancement in control methodologies [2].

4. Conclusion

In this article, a detailed introduction and study of the basic structure and working principle of inkjet printers were discussed, and comparisons and differences between different printers and inkjet printers were listed. Afterwards, a detailed study was conducted on the stepper motor in the printer, including its basic structure, stator, and rotor. Different types, hybrid stepper motors. The working principle is based on the law of electromagnetic induction. Finally, an analysis and optimization were conducted on the existing problems of stepper motors. Including simulation experiments to optimize the position accuracy of ship stepper motors and particle swarm optimization-based speed control of stepper motors, ensuring their stability in operation

In summary, this study provides a theoretical basis and practical guidance for the application and optimization of stepper motors in inkjet printers. It is expected that more advanced technologies and materials will be applied in inkjet printing technology in the future to improve the efficiency of stepper motors and solve existing problems, in order to promote the continuous progress of inkjet printing technology. Hope these research results will provide useful contributions to improving printer performance and reducing production costs

References

[1] *Shah M A, Lee D G, Lee B Y, et al. Classifications and applications of inkjet printing technology: A review. IEEE Access, 2021, 9: 140079-140102.*

[2] *Döring M. Ink-jet printing. IEEE Trans. ED, 1973, 20: 14-19.*

[3] *Kretschmer J. The Ink Cartridge as a Major Component of an InkJet System. NIP & Digital Fabrication Conference. Society of Imaging Science and Technology, 2001, 17: 43-48.*

[4] *Yang P, Zhang X, Chen J. Design of Control System for Inkjet Printer. Journal of Physics: Conference Series. IOP Publishing, 2021, 2037(1): 012056.*

[5] *Cong X, Biao L, Hengyang W. Software Design of Inkjet Printer Management System Based on Android. 2020 2nd International Conference on Information Technology and Computer Application (ITCA). IEEE, 2020: 655-659.*

[6] *Byeon J H, Kim J W. Particle emission from laser printers with different printing speeds. Atmospheric Environment, 2012, 54: 272-276.*

[7] *Kukla M, Tarkowski P, Malujda I, et al. Determination of the torque characteristics of a stepper motor. Procedia Engineering, 2016, 136: 375-379.*

[8] *Balaji S, Muthukumaran V, Senthilkumar K M, et al. An overview of stepper motors. The opportunities of uncertainties: flexibility and adaptation needed in current climate, 2021, 2: 265.*

[9] *Derammelaere S, Debruyne C, De Belie F, et al. Load angle estimation for two-phase hybrid stepping motors. IET Electric power applications, 2014, 8(7): 257-266.*

[10] *Jeong Y W, Lee Y, Chung C C. A survey of advanced control methods for permanent magnet stepper motors. Journal of Marine Science and Technology, 2020, 28(5): 2.*

[11] *Zhang Xinjun Optimization Control Method for Position Accuracy of Ship Stepper Motor. Ship Science and Technology, 2021, 43 (14): 94-96.*

DOI: 10.54254/2753-8818/80/2025.GL20478

[12] Wang S, Xin X, Ren J, et al. Digital Control System for Stepping Motor Driver Chip[C]//Journal of Physics: Conference Series. IOP Publishing, 2022, 2221(1): 012003.

[13] Jia Mengmeng, Hu Dongfang, Xu Qiyue, etc Research on the Speed Control Method of Stepper Motor Optimized by Particle Swarm Optimization Algorithm. Journal of China Jiliang University, 2022, 33 (02): 221-227.

[14] Wang D, Tan D, Liu L. Particle swarm optimization algorithm: an overview. Soft computing, 2018, 22(2): 387-408.

[15] Borase R P, Maghade D K, Sondkar S Y, et al. A review of PID control, tuning methods and applications. International Journal of Dynamics and Control, 2021, 9: 818-827.